

Quantec Accessible Toilet Reset Point c/w Confidence Sounder

Part No. **QT605S**



Overview

- An addressable Quantec reset point c/w confidence sounder specifically designed for use in BS8300 compliant accessible toilet alarm applications.
- Includes a red/green reassurance LED and RESET button with Braille text for cancelling calls.
- Can be interfaced to a Quantec ceiling pull (installed inside the WC) and overdoor light c/w sounder (installed outside the WC).
- Will generate a Standard call tone when its ceiling pull is activated and an intermittent 'call acknowledgement' tone when the call is accepted at a Quantec display (to let users know help is on the way).
- Also available as part of our QT951 Accessible Toilet Alarm kit.



More Information

Technical Specifications

Power requirements	Nominal 24V DC (from Quantec Controller/Network)
Quiescent current	Less than 5mA.
Indicators	Red/green confidence LED.
Controls	Reset button.
Connections	Net +: Net -; R; G; L+; SW
Expansion connections	R (red), G (green), L+ (local +Ve) and SW (switch) terminals allow the connection of a dummy/extender ceiling pull and dummy/extender overdoor light c/w sounder.



Onboard 6.35mm Remote Jack Socket	No.
Onboard Sounder	Yes - sounds Quantec's standard call tone when its dummy/extender ceiling pull is activated and a slow intermittent tone when the call is Accepted at a Quantec display.
Onboard Infrared Receiver	No.
Product dimensions (mm)	87 W x 87 H x 23 D mm. Can be mounted on a standard UK 25mm single gang flush or surface back box.
Construction & finish	Plastic.
IP Rating	IP40.
Weight	66g.
Operating conditions/temperature	-5°C to +40°C. Max relative humidity: 95%.



T 01942 322744 E sales@c-tec.co.uk
F 01942 829867 W www.c-tec.com



C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom