

Chair Exit Mat

Part No. **QT634**



Overview

- Designed to trigger a call by sensing the pressure change when a patient exits a chair.
- Connects to Quantec via the remote jack socket on a QT637 Enuresis/General Purpose Interface Socket or QT636 Interface Unit.
- To reduce the risk of nuisance calls, the QT637 includes circuitry that prevents a momentary change in pressure such as a patient quickly changing position from triggering a call.
- Measures 400mm x 250mm and is supplied with a 2m lead and normally closed right angled jack plug.

More Information

Technical Specifications

Compatibility	Must be used in conjunction with a QT637 Quantec Enuresis Sensor/General Purpose Interface Socket or QT636 Interface Socket.
Connections	6.35mm (quarter inch) jack plug.
Product dimensions (mm)	378mm W x 248mm H. Includes a 2m lead.
Construction & finish	Plastic.
IP Rating	TBC.
Weight	150g
Operating conditions/temperature	-5°C to +40°C. Max relative humidity: 95%.